



Image shown may not reflect actual package.

PRIME 220 kW 275 kVA 50 Hz 1500 rpm 400 Volts

Caterpillar is leading the power generation marketplace with Power Solutions engineered to deliver unmatched flexibility, expandability, reliability, and cost-effectiveness.

FEATURES

FUEL/EMISSIONS STRATEGY

- Low Fuel consumption

FULL RANGE OF ATTACHMENTS

- Wide range of bolt-on system expansion attachments, factory designed and tested
- Flexible packaging options for easy and cost effective installation

COMPLETE, READY-TO-RUN SYSTEM

- Fully configured generator set
- Full range of attachments and options available

ENCLOSURES (Optional)

- Weather protective

SINGLE-SOURCE SUPPLIER

- Fully prototype tested with certified torsional vibration analysis available

WORLDWIDE PRODUCT SUPPORT

- Cat dealers provide extensive post sale support including maintenance and repair agreements
- Cat dealers have over 1,800 dealer branch stores operating in 200 countries
- The Cat® S•O•SSM program cost effectively detects internal engine component condition, even the presence of unwanted fluids and combustion by-products

CAT® 3406C TA DIESEL ENGINE

- High efficiency, four-stroke-cycle engine designed for thousands of trouble-free hours of operation
- Field-proven in thousands of applications

CAT GENERATOR

- Matched to the performance and output characteristics of Cat engines
- Load adjustment module provides engine relief upon load impact and improves load acceptance and recovery time
- UL 1446 Recognized Class H insulation

CAT EMCP 4 CONTROL PANELS

- Simple user friendly interface and navigation
- Scalable system to meet a wide range of customer needs
- Integrated Control System and Communications Gateway

PRIME 220 kW 275 kVA

50 Hz 1500 rpm 400 Volts



FACTORY INSTALLED STANDARD & OPTIONAL EQUIPMENT

System	Standard	Optional
Air Inlet	• Air cleaner	
Cooling	• Package mounted radiator	
Exhaust	• Exhaust flange outlet	<input type="checkbox"/> Industrial <input type="checkbox"/> Residential <input type="checkbox"/> Critical Mufflers
Fuel	• Primary fuel filter with integral water separator • Secondary fuel filters • Fuel priming pump	
Generator	• Matched to the performance and output characteristics of Cat engines • Load adjustment module provides engine relief upon load impact and improves load acceptance and recovery time • IP23 protection	<input type="checkbox"/> Oversize and premium generators <input type="checkbox"/> Permanent magnet excitation (PMG) <input type="checkbox"/> Internal excited (IE) <input type="checkbox"/> Anti-condensation space heaters
Power Termination	• Bus bar	<input type="checkbox"/> Circuit breakers, UL listed <input type="checkbox"/> Circuit breakers, IEC compliant
Control Panel	• EMCP 4 Genset Controller	<input type="checkbox"/> EMCP 4.2 <input type="checkbox"/> EMCP 4.3 <input type="checkbox"/> EMCP 4.4 <input type="checkbox"/> Local and remote annunciator modules <input type="checkbox"/> Load share module <input type="checkbox"/> Digital I/O module <input type="checkbox"/> Remote monitoring software
Mounting	• Rubber vibration isolators	
Starting/Charging	• 24 volt starting motor • Batteries	<input type="checkbox"/> Battery chargers <input type="checkbox"/> Oversize batteries <input type="checkbox"/> Jacket water heater <input type="checkbox"/> Heavy duty starting system <input type="checkbox"/> Charging alternator
General	• Paint - Caterpillar Yellow except rails and radiators gloss black	The following options are based on regional and product configuration: <input type="checkbox"/> Seismic Certification per Applicable Building Codes: IBC 2000, IBC 2003, IBC 2006, IBC 2009, CBC 2007 <input type="checkbox"/> UL 2200 package <input type="checkbox"/> EU Certificate of Conformance (CE) <input type="checkbox"/> CSA Certification <input type="checkbox"/> EEC Declaration of Conformity <input type="checkbox"/> Narrow, wide or skid base <input type="checkbox"/> Sound attenuated, weather protective or high ambient weather protective enclosures <input type="checkbox"/> Single or dual wall integral fuel tanks <input type="checkbox"/> Single or dual wall sub-base fuel tanks <input type="checkbox"/> Integral & sub-base UL listed dual wall fuel tanks <input type="checkbox"/> Automatic transfer switches (ATS)

PRIME 220 ekW 275 kVA

50 Hz 1500 rpm 400 Volts



SPECIFICATIONS

CAT GENERATOR

Frame size.....LC5014J
Excitation..... Self Excitation
Pitch..... 0.6666
Number of poles..... 4
Number of bearings..... Single bearing
Number of Leads..... 012
Insulation..... UL 1446 Recognized Class H with tropicalization and antiabrasion
- Consult your Caterpillar dealer for available voltages
IP Rating..... IP23
Alignment..... Pilot Shaft
Overspeed capability..... 150
Wave form Deviation (Line to Line)..... 002.00
Voltage regulator..... Three phase sensing
Voltage regulation..... Less than +/- 1/2% (steady state)
Less than +/- 1% (no load to full load)

CAT DIESEL ENGINE

3406C TA, I-6, 4-Stroke Water-cooled Diesel
Bore..... 137.20 mm (5.4 in)
Stroke..... 165.10 mm (6.5 in)
Displacement..... 14.64 L (893.39 in³)
Compression Ratio..... 14.5:1
Aspiration..... TA
Fuel System
Governor Type..... Hydra-mechanical

CAT EMCP 4 SERIES CONTROLS

EMCP 4 controls including:

- Run / Auto / Stop Control
- Speed and Voltage Adjust
- Engine Cycle Crank
- 24-volt DC operation
- Environmental sealed front face
- Text alarm/event descriptions

Digital indication for:

- RPM
- DC volts
- Operating hours
- Oil pressure (psi, kPa or bar)
- Coolant temperature
- Volts (L-L & L-N), frequency (Hz)
- Amps (per phase & average)
- ekW, kVA, kVAR, kW-hr, %kW, PF (4.2 only)

Warning/shutdown with common LED indication of:

- Low oil pressure
- High coolant temperature
- Overspeed
- Emergency stop
- Failure to start (overcrank)
- Low coolant temperature
- Low coolant level

Programmable protective relaying functions:

- Generator phase sequence
- Over/Under voltage (27/59)
- Over/Under Frequency (81 o/u)
- Reverse Power (kW) (32) (4.2 only)
- Reverse reactive power (kVAR) (32RV)
- Overcurrent (50/51)

Communications:

- Four digital inputs (4.1)
- Six digital inputs (4.2 only)
- Four relay outputs (Form A)
- Two relay outputs (Form C)
- Two digital outputs
- Customer data link (Modbus RTU) (4.2 only)
- Accessory module data link (4.2 only)
- Serial annunciator module data link (4.2 only)
- Emergency stop pushbutton

Compatible with the following:

- Digital I/O module
- Local Annunciator
- Remote CAN annunciator
- Remote serial annunciator

PRIME 220 ekW 275 kVA

50 Hz 1500 rpm 400 Volts



TECHNICAL DATA

Open Generator Set - - 1500 rpm/50 Hz/400 Volts	DM7524	
Low Fuel Consumption		
Generator Set Package Performance Genset Power rating @ 0.8 pf Genset Power rating with fan	275 kVA 220 ekW	
Coolant to aftercooler Coolant to aftercooler temp max	50 ° C	122 ° F
Fuel Consumption 100% load with fan 75% load with fan 50% load with fan	64.2 L/hr 49.9 L/hr 36.0 L/hr	17.0 Gal/hr 13.2 Gal/hr 9.5 Gal/hr
Cooling System¹ Air flow restriction (system) Air flow (max @ rated speed for radiator arrangement) Engine Coolant capacity with radiator/exp. tank Engine coolant capacity Radiator coolant capacity	0.12 kPa 522 m ³ /min 57.8 L 20.8 L 37.0 L	0.48 in. water 18434 cfm 15.3 gal 5.5 gal 9.8 gal
Inlet Air Combustion air inlet flow rate	16.5 m ³ /min	582.7 cfm
Exhaust System Exhaust stack gas temperature Exhaust gas flow rate Exhaust flange size (internal diameter) Exhaust system backpressure (maximum allowable)	563.6 ° C 48.3 m ³ /min 152.4 mm 6.7 kPa	1046.5 ° F 1705.7 cfm 6.0 in 26.9 in. water
Heat rejection Heat rejection to atmosphere from generator	16.3 kW	927.0 Btu/min
Alternator² Motor starting capability @ 30% voltage dip Frame Temperature Rise	586 skVA LC5014J 125 ° C	225 ° F
Lube System Sump refill with filter	38.0 L	10.0 gal

¹ For ambient and altitude capabilities consult your Cat dealer. Air flow restriction (system) is added to existing restriction from factory.

² UL 2200 Listed packages may have oversized generators with a different temperature rise and motor starting characteristics. Generator temperature rise is based on a 40°C ambient per NEMA MG1-32.

PRIME 220 ekW 275 kVA

50 Hz 1500 rpm 400 Volts



RATING DEFINITIONS AND CONDITIONS

Applicable Codes and Standards: AS1359, CSA C22.2 No 100-04, UL142, UL489, UL601, UL869, UL2200, NFPA 37, NFPA 70, NFPA 99, NFPA 110, IBC, IEC60034-1, ISO3046, ISO8528, NEMA MG 1-22, NEMA MG 1-33, 72/23/EEC, 98/37/EC, 2004/108/EC

Prime - Output available with varying load for an unlimited time. Average power output is 70% of the prime power rating. Typical peak demand is 100% of prime rated ekW with 10% overload capability for emergency use for a maximum of 1 hour in 12. Overload operation cannot exceed 25 hours per year.

Ratings are based on SAE J1349 standard conditions. These ratings also apply at ISO3046 standard conditions. **Fuel Rates** are based on fuel oil of 35° API (16° C or 60° F) gravity having an LHV of 42 780 kJ/kg (18,390 Btu/lb) when used at 29° C (85° F) and weighing 838.9 g/liter (7.001 lbs/U.S. gal.). **Additional Ratings** may be available for specific customer requirements. Consult your Cat representative for details.



RLP
INDUSTRIES LTD